


## SC-4000 Lite



Cadru tratat pentru a preveni ruginirea



Alternator produs si patentat de Senci



Filtru de aer patentat

Generator Senci	SC-4000 Lite
Voltaj	230V
Freventa	50 Hz
Putere max.	3.8 kW
Putere in regim continuu	3.3 kW
Regulator de tensiune	AVR
Tip motor Senci	SC170FB
Putere motor Senci	7cp/223cmc
Rotatii motor	3000 rpm
Demaraj	la sfoara
Racire	Aer
Carburant	Benzina
Capacitate rezervor	15 l
Autonomie (100% putere)	8.5 ore
Autonomie (50% putere)	13.5 ore
Zgomot la 7 metri	97 dB
Dimensiuni (L x l x h mm)	592 x 460 x 470
Greutate utilaj	50 kg



Panou comanda

### Echipare standard:

Alternator Senci de calitate superioara  
Alerta nivel ulei scazut cu oprire automata a motorului  
Sensor de suprasarcina cu auto-oprire  
Filtru de aer nou, mai mic cu un design deosebit ce reduce consumul de ulei si creste puterea generatorului  
Silentios si prietenos cu mediul  
Regulator de tensiune AVR  
Portabil, compact, cadru rezistent  
Pentru uz casnic dar si comercial  
Panou de control rezistent la ploaie si praf  
2 prize 230V 16A  
Multimetru digital cu afisare: tensiune, frecventa, contor ore



[www.italiastar.ro](http://www.italiastar.ro)

**SOLICITA ACUM  
OFERTA  
PERSONALIZATA!**

Italia Star Com Due S.R.L.  
Autostrada Bucuresti - Pitesti km. 13.2  
Loc. Chiajna - Ilfov  
Tel: 021.433.03.27  
Fax: 021.433.03.26  
info@italiastar.ro www.italiastar.ro